

www.ti.com

SNOSBT3H-JANUARY 2000-REVISED MARCH 2013

LM158/LM258/LM358/LM2904 Low Power Dual Operational Amplifiers

Check for Samples: LM158-N, LM258-N, LM2904-N, LM358-N

FEATURES

- Available in 8-Bump DSBGA Chip-Sized Package, (See AN-1112 (SNVA009))
- Internally Frequency Compensated for Unity Gain
- Large DC Voltage Gain: 100 dB •
- Wide Bandwidth (Unity Gain): 1 MHz (Temperature Compensated)
- Wide Power Supply Range:
 - Single Supply: 3V to 32V
 - Or Dual Supplies: ±1.5V to ±16V
- Very Low Supply Current Drain (500 µA)—Essentially Independent of Supply Voltage
- Low Input Offset Voltage: 2 mV
- Input Common-Mode Voltage Range Includes . Ground
- **Differential Input Voltage Range Equal to the Power Supply Voltage**
- Large Output Voltage Swing

UNIQUE CHARACTERISTICS

- In the Llinear Mode the Input Common-Mode Voltage Range Includes Ground and the Output Voltage Can Also Swing to Ground, even though Operated from Only a Single Power Supply Voltage.
- The Unity Gain Cross Frequency is Temperature Compensated.
- The Input Bias Current is also Temperature Compensated.

ADVANTAGES

- **Two Internally Compensated Op Amps** •
- **Eliminates Need for Dual Supplies**
- Allows Direct Sensing Near GND and Vout Also Goes to GND
- Compatible with All Forms of Logic
- **Power Drain Suitable for Battery Operation**

DESCRIPTION

The LM158 series consists of two independent, high gain, internally frequency compensated operational amplifiers which were designed specifically to operate from a single power supply over a wide range of voltages. Operation from split power supplies is also possible and the low power supply current drain is independent of the magnitude of the power supply voltage.

Application areas include transducer amplifiers, dc gain blocks and all the conventional op amp circuits which now can be more easily implemented in single power supply systems. For example, the LM158 series can be directly operated off of the standard +5V power supply voltage which is used in digital systems and will easily provide the required interface electronics without requiring the additional ±15V power supplies.

The LM358 and LM2904 are available in a chip sized package (8-Bump DSBGA) using TI's DSBGA package technology.



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet. All trademarks are the property of their respective owners.